

## signotec Omega (NFC)

# Highlights & Data Sheet











### **HIGHLIGHTS**

- 5" (12,8 cm) full-colour display with integrated palm-rest.
- Signature capturing with 500 Hz 4D samples and 1.024 pressure stages (x, y, z, t).
- Unique RSA-signature creation and RSA-encryption methods inside the pad.
- Self-sufficient slideshow with up to 10 pictures.
- No special pen required (cheap replacement available).
- Battery-free pen with changeable pen tip.
- "Content Signing" allows signing the LCD-content with the captured signature.
- Secure Mode to display the signature on the screen in real-time.
- Optionally available Near Field Communication (NFC) Sensor.
- Delivery comes with completely assembled USB cable, pen and cord.
- Including free of charge software packages and SDK for several programming languages.









## **TECHNICAL DATA**

| General data      |  |
|-------------------|--|
| Dimensions        | 180 x 191 x 15 mm (H x W x T)  |
| Casing colours    | Upper shell: RAL 7021, black-grey<br>Lower shell: RAL 7021, black-grey |
| Cable port        | USB  |
| Cable length      | Approx. 2 meters, optional 5 meters                                    |
| Power consumption | 430mA; Standby 13mA (HID/WinUSB) and 8mA (FTDI)                        |
| Power supply      | USB  |
| Status-LED        | 2 coloured and freely programmable LEDs                                |
| Stand             | Mounting stand on the backside, compatible Multigrip™ plate available  |
| Weight            | Approx. 320 grams (incl. cable)  |
| Warranty          | 2 years, optional extension up to 5 years.                             |
| Country of origin | Germany  |

| Display                    |  |
|----------------------------|--|
| Туре                       | Full-Colour-TFT  |
| Size                       | 5" (12,8 cm)   |
| Colour space               | 65.536   |
| Backlight                  | LED-Backlight, brightness: 250 cd/m <sup>2</sup>                   |
| Configuration of backlight | The backlight can be configured with an API or configuration file. |
| Resolution                 | 640 x 480 pixels ≙ 161 x 161 ppi                                   |
| Pixel size                 | 0,0529 x 0,1587 mm   |
| Visible area               | 101 x 76 mm  |
| Line of sight              | 6 o'clock  |
| Scroll-function            | Maximum size of the displayed image: 640 x 960 pixels.             |

| Sensor                      |  |
|-----------------------------|--|
| Туре                        | Resistive Touch Panel (RTP)  |
| Active signing area         | 100 x 75 mm  |
| Resolution                  | 4.096 x 4.096 pixels ≙ 1.388 x 1.040 ppi   |
| Linearity                   | ±1,5 % in x-, y- and z- direction  |
| Method of input             | Special sensor for pen input   |
| Surface                     | Special foil surface with wear-protection.   |
| Surface hardness            | 3H   |
| Life expectancy             | Approx. 1 million signatures   |
| Pressure stages             | 1.024 pressure stages  |
| Output rate of coordinates  | 500 Hz 4D-samples (x, y, z, t)   |
| Internal sampling rate      | 6.000 samples per second   |
| Stability of output rate    | Constant through integrated quartz   |
| Pen                         | Battery-less pen with special, springy mine (changeable).                          |
| Life expectancy of the pen  | Approx. 150.000 signatures at 250 Gramm pressure and 2,5 cm length.                |
| Pen tilt angle              | n/a  |
| Possible height of the pen  | n/a  |
| Pen attachment              | Highly flexible textile-cord and horizontal pen holder. (assembled at the factory) |
| © 2000 - 2020 signotec GmbH | Data Sheet signotec Omega (NFC) Page 3 of 5  |



| Near Field Communication (NFC) |   |
|--------------------------------|---|
| Availability                   | Optional, Integration below the hand rest.  |
| Туре                           | NXP PR533   |
| Integration                    | Microsoft or Linux Smart Card API   |
| Power consumption              | The power consumption is enhanced by approx. 90mA with NFC-Reader active.   |
| Compatibility                  | <ul> <li>Read / write functionality compatible with the tag types ISO / IEC 14443 A &amp; B, MIFARE ™, FeliCa and NFC Forum (Jewel, MIFARE Ultra-light, FeliCa, FeliCalite, MIFARE DESFire) and supports I-Class (modulation from Picopass B type) Passive Initiator ISO18092</li> <li>Corresponding to the German eID, ICAO and EMVCo 2.1</li> <li>Supports PCSC Part 3 Release 2.01.07</li> <li>Integrated support for the MIFARE-Reader</li> <li>CCID-Protocol supported, validated with Microsoft Windows and Linux CCID native Drivers.</li> </ul> |

| Connection Types    |  |
|---------------------|--|
| USB                 | HID-USB and WinUSB   |
| Serial              | Optional with internal USB-Serial-Converter (VCOM-Port) using FTDI or chargeable VCOM-Port-Driver. |
| USB-Standby-Support | Yes, if the corresponding signal is given, the device switches off.                                |
| Ethernet            | Yes, with an optionally available USB-to-Ethernet adapter.   |

| Driver and Software |   |
|---------------------|---|
| Driver              | No special driver is required for a USB connection.   |
| Plug and Play       | Yes, available for all connection types.              |
| SDK (API)           | SDK/API free of charge including updates and support. |
| Tools               | Tools free of charge including updates and support.   |
| Software            | Further chargeable software available.                |

| System environment         |   |
|----------------------------|---|
| Operating System           | Windows 7 and newer, Windows Server 2012 and newer, 32- and 64-Bit, Linux |
| Terminal Server and Citrix | Compatible with Windows Remote Desktop and Citrix ICA                     |
| Citrix Virtual Channel     | Optionally available  |

| Security mechanisms                  |  |
|--------------------------------------|--|
| Data transfer                        | AES-256 encrypted data transfer between host and pad via RSA key exchange.                         |
| Encryption                           | RSA-Encryption unit inside the pad.  |
| Firmware                             | Flash memory is protected against data theft.  |
| Secure Mode                          | Real-time display of the signature without usable biometrics.                                      |
| Signature unit                       | RSA signature creation unit in the pad.  |
| Key storage                          | Creation and storage of certificates in the pad.   |
| Key size                             | 4096 Bit   |
| Certificate Signing Request (CSR)    | CSR can be generated in the pad and extracted.   |
| Trusted certificates                 | The CSR can be signed by a root authority. Additional information: <u>eIDAS Pad Signature Seal</u> |
| Supported Hash-algorithms            | SHA-1, SHA-256 und SHA-512   |
| signotec "Content-Signing"           | Yes  |
| Protection against forceful break in | The casing can be glued optionally.  |



| Miscellaneous                                  |   |
|--|---|
| Transport protection                           | No  |
| Individualization                              | Change of casing colour and logo print (on request).  |
| Slideshow                                      | A standby slideshow with up to 10 images is freely configurable.  |
| Certifications and standards                   | CE, FCC, DIN EN 60950-1, DIN EN 61000-6-1, EN 61000-6-3, EN 55022, EN 55024   |
| RoHS   | RoHS-compliant according to EU-regulations.   |
| WEEE-RegNo. (German register for used devices) | DE 41995888   |
| Packaging law RegNo.:                          | DE 3470684644700  |
| Serial number                                  | Unique and retrievable, internal serial number.   |
| Device label                                   | There is a label on the packaging and the device with information regarding the article number, hardware revision and serial number, including a barcode. |

| Operating- and storage conditions      |                        |
|--|------------------------|
| Operating temperature                  | -10°C to +60°C         |
| Storage temperature                    | -25°C to +70°C         |
| Air humidity for operation and storage | <= 90%, non-condensing |
| Air pressure for operation and storage | > 700 hPa              |
| Degree of protection                   | IP 52                  |

| Reliability / Quality assurance         |  |
|---|--|
| Quality test                            | Individual testing of devices with test log.                               |
| High temperature test of the components | 240 hours at 80°C  |
| Low temperature test of the components  | 240 hours at - 40°C  |
| Humidity test of the components         | 240 hours at 60°C and 90% humidity   |
| Thermal shock test of the components    | 30 minutes at – 40°C and directly 30 minutes at + 80°C (10x in succession) |

| Article numbers     |   |
|---------------------|---|
| ST-CE1075-2-U100    | Signotec Omega with HID-USB- 2 m  |
| ST-CE1075-2-FT100   | signotec Omega FTDI (VCOM) and approx. USB – 2 m (USB2serial)   |
| ST-CE1075-5-U100    | signotec Omega with HID-USB – 5 m   |
| ST-CE1075-5-FT100   | signotec Omega FTDI (VCOM) and approx. USB – 5 m (USB2serial)   |
| ST-CE1075-2-UNFC100 | signotec Omega NFC, HID-USB with integrated NFC-Reader, 2 m<br>Note: For technical reasons, the hybrid system with NFC reader is only<br>available with a 2 m cable length. |

#### Copyright

Copyright © 2000 - 2020 signotec GmbH

All rights reserved. This documentation and the components described therein are copyrighted products of signotec GmbH Ratingen in Germany. Partial or full reproduction is only permitted with the written consent of signotec GmbH. All hardware and software names used are trade names and / or trademarks of the respective manufacturers / owners. Subject to changes at any time. We accept no liability for errors in the documentation.

| © 2000 - 2020 signotec GmbH Data Sheet signotec Omega (NFC) Page 5 |
|--|
|--|